

Channels en Repositories in Spacewalk

Nadat je [een Spacewalk server hebt geïnstalleerd](#) moet je deze nog van channels voorzien.

Het verdient aanbeveling even goed na te denken over de layout van je channels.

mijn setup ziet er zo uit :

```
centos_6-base
|_ centos_6-updates
|_ epel_6

centos_7-base
|_ centos_7-updates
|_ epel_7
```

Base channel

[Maak een base channel aan door in het boven menu Channels](#) te kiezen en vervolgens in het zij menu **Manage Software Channels** en druk op het blauwe **+ Create Channel**

The screenshot shows the Spacewalk web interface. The top navigation bar includes links for Knowledgebase, Documentation, and user roles (admin, etc.). The main navigation menu has tabs for Overview, Systems, Errata, Channels (selected), Audit, Configuration, and a status bar showing '0 systems selected' with 'Manage' and 'Clear' buttons. Below this, there are links for Schedule and Users. The left sidebar contains a tree view with 'Manage Software Channels' highlighted. The main content area is titled 'Software Channel Management' and includes links to '+ Create Channel' and 'Clone Channel'. It states that no software channels are currently owned by the organization. Below this, there is a table with columns 'Channel Name' and 'Packages', which currently shows 'No channels found.' The footer contains copyright information for Red Hat, Inc. and links to privacy and legal statements.

Channel Name	Packages
No channels found.	

[Vul de naam en label in, geen idee waarom er twee zijn, maar volgens de instructies mag er in geen](#)

van beide hoofdletters of spaties. Hou ze voor het gemak gelijk.

The screenshot shows the Spacewalk web interface. The top navigation bar includes links for Knowledgebase, Documentation, and user roles (admin, etc.). The main navigation menu has tabs for Overview, Systems, Errata, Channels (selected), Audit, Configuration, and a summary bar showing '0 systems selected' with 'Manage' and 'Clear' buttons. Below the navigation, a sidebar on the left lists options like Software Channels, Package Search, Manage Software Channels (highlighted), Manage Software Packages, Manage Repositories, and Distribution Channel Mapping. The main content area is titled 'Create Software Channel' and contains 'Basic Channel Details'. It provides instructions on creating or editing channels, including rules for channel names and labels. The form fields are filled with: Channel Name*: centos_7-x86_64, Channel Label*: centos_7-x86_64, Parent Channel: None, Architecture: x86_64, Yum Repository Checksum Type: sha1. A tip explains that sha1 offers the widest compatibility, while sha-256 offers higher security for newer clients. The Channel Summary* field contains 'Base Channel for CentOS 7'.

Create Software Channel

Basic Channel Details

Create or edit software channels from this page.

If the parent channel is set to 'none', the channel is a base channel. Otherwise, the channel is a child of the specified channel.

Channel name and label are required.
They each must be at least 6 characters in length.
Channel name must not be longer than 256 characters and channel label must not be longer than 128 characters.
Channel name must begin with a letter and channel label may begin with a letter or digit.
They each must not begin with rhn, redhat or red hat.
They each must contain only lowercase letters, hyphens ('-'), periods ('.'), underscores ('_'), and numerals.
Channel name may also contain spaces, parentheses () and forward slashes ('/').

Channel summary is also required and must not exceed 500 characters.

Channel Name*:

Channel Label*:

Parent Channel:

Architecture:

Yum Repository Checksum Type:

Tip: sha1 offers the widest compatibility with clients. sha-256 offers higher security, but is compatible only with newer clients: Fedora 11 and newer, or Enterprise Linux 6 and newer.

Channel Summary*:

Scroll naar beneden, daar moet de GPG informatie worden ingevuld waar de rpm's uit de repository mee gesigned zijn.

Je krijgt deze informatie het eenvoudigst door de gpg-key te downloaden naar een linux machine, de spacewalk server zelf is een prima optie aangezien in afgeschermdde omgevingen dit überhaupt de enige server is die met de repo server die als bron gekozen is kan communiceren.

installeer wget :yum install wget

haal de gpgkey op:

```
cd /tmp
```

```
wget
```

```
http://ftp.nluug.nl/ftp/pub/os/Linux/distr/CentOS/7/os/x86_64/RPM-GPG-KEY-CentOS-7
```

en haal de nodige gegevens uit de key door:

```
gpg --with-fingerprint RPM-GPG-KEY-CentOS-7
```

de output ziet er ongeveer zo uit. Het gatal na de slash is het key ID

```
pub 4096R/F4A80EB5 2014-06-23 CentOS-7 Key (CentOS 7 Official Signing Key)
<security@centos.org>
    Key fingerprint = 6341 AB27 53D7 8A78 A7C2 7BB1 24C6 A8A7 F4A8 0EB5
```

[vul dit in en druk op](#) **Create Channel:**

Channel Access Control

Per-User Subscription Restrictions:

☒ All users within your organization may subscribe to this channel.

☐ Only selected users within your organization may subscribe to this channel.

Organization Sharing:

☒ This channel is **private** and cannot be accessed by any other organization.

☐ This channel is **protected** and may only be accessed by specific [trusted organizations](#).

☐ This channel is **public** and may be accessed by any of the [trusted organizations](#) trusted by this organization.

Security: GPG

GPG key URL:

GPG key ID:

Example: DB42A60E

GPG key Fingerprint:

Example: CA20 8686 2BD6 9DFC 65F6 ECC4 2191 80CD DB42 A60E

[Create Channel](#)


Copyright © 2002-15 Red Hat, Inc. All rights reserved. [Privacy statement](#) : [Legal statement](#) : [redhat.com](#)

Spacewalk release 2.6



nu is het tijd om een repository aan te maken, aan het channel te koppelen en te syncen met de upstream. kies in het zij menu **Manage Repositories** en druk rechs boven op **+Create Repository**

[vul vervolgens de velden in](#) en druk op **Create Repository**:



The screenshot shows the Spacewalk web interface. The top navigation bar includes links for Knowledgebase, Documentation, and user settings (admin). A search bar is present with the text 'Systems' and a search icon. Below this is a main navigation menu with tabs: Overview, Systems, Errata, Channels (selected), Audit, Configuration, 0 systems selected, Manage, and Clear. Further down are links for Admin and Help. On the left side, there is a sidebar menu with options: > Software Channels, > Package Search, > Manage Software Channels (highlighted), > Manage Software Packages, > Manage Repositories, and > Distribution Channel Mapping. The main content area is titled 'Create Repository' with an information icon. It contains several form fields: 'Repository Label*' with the value 'centos_7-x86_64-nluug', 'Repository URL*' with the value 'http://ftp.nluug.nl/ftp/pub/os/Linux/distr/CentOS/7/os/x86_64/', 'Repository Type*' with a dropdown menu showing 'yum', 'SSL CA Certificate' with a dropdown menu showing 'None', 'SSL Client Certificate' with a dropdown menu showing 'None', and 'SSL Client Key' with a dropdown menu showing 'None'. There is also a 'Filters' section with an empty text box. A tip at the bottom reads 'Tip: -zsh*,kernel +zsh-html'. A green 'Create Repository' button is at the bottom of the form.

SPACEWALK

Knowledgebase Documentation admin

Systems Search

Overview Systems Errata **Channels** Audit Configuration 0 systems selected **Manage** Clear

Schedule Users

Admin Help

> Software Channels

> Package Search

> **Manage Software Channels**

> Manage Software Packages

> **Manage Repositories**

> Distribution Channel Mapping

i Create Repository

Create Repository

Repository Label*: centos_7-x86_64-nluug

Repository URL*: http://ftp.nluug.nl/ftp/pub/os/Linux/distr/CentOS/7/os/x86_64/

Repository Type*: yum

SSL CA Certificate: None

SSL Client Certificate: None

SSL Client Key: None

Filters

Tip: -zsh*,kernel +zsh-html

Create Repository

Vervolgt stap is de repository aan het channel koppelen. In **Manage Software Channels** klik op de channel waar de repository bij hoort, kies het tabblad **Repositories** selecteer de net gemaakte repository en druk op **Update Repositories**

The screenshot shows the Spacewalk web interface. The top navigation bar includes 'Overview', 'Systems', 'Errata', 'Channels' (selected), 'Audit', 'Configuration', '0 systems selected', 'Manage', and 'Clear'. Below this is a sidebar with 'Admin' and 'Help' links, and a list of software management options. The main content area displays the 'centos_7-x86_64' channel details, with the 'Repositories' tab selected. A message at the top indicates that the repository information was successfully updated. The 'Channel Repositories' section shows a list of repositories with 'centos_7-x86_64-nluug' selected. The 'Update Repositories' button is visible at the bottom right.

Vervolgens is het tijd om het channel te syncen met de upstream repository. Log in op de spacewalk server en doe:

```
spacewalk-repo-sync -c centos_7-x86_64
```

Dit kan overigens even duren.

```
07:15:26 =====
07:15:26 | Channel: centos_7-x86_64
07:15:26 =====
07:15:26 Sync of channel started.
07:15:26 Repo URL:
http://ftp.nluug.nl/ftp/pub/os/Linux/distr/CentOS/7/os/x86_64/
07:15:29 Packages in repo:          9363
07:15:48 Packages already synced:    0
07:15:48 Packages to sync:          9363
```

```
07:15:48 1/9363 : 389-ds-base-1.3.5.10-11.el7-0.x86_64
07:16:19 2/9363 : 389-ds-base-devel-1.3.5.10-11.el7-0.x86_64
07:16:20 3/9363 : 389-ds-base-libs-1.3.5.10-11.el7-0.x86_64
...

...
14:30:07 9361/9363 : zziplib-devel-0.13.62-5.el7-0.x86_64
14:30:16 9362/9363 : zziplib-devel-0.13.62-5.el7-0.i686
14:30:18 9363/9363 : zziplib-utils-0.13.62-5.el7-0.x86_64
14:30:19 Linking packages to channel.
14:30:30 Repo http://ftp.nluug.nl/ftp/pub/os/Linux/distr/CentOS/7/os/x86_64/
has comps file comps.xml.
14:30:30 Repo http://ftp.nluug.nl/ftp/pub/os/Linux/distr/CentOS/7/os/x86_64/
has 0 errata.
14:30:30 Sync of channel completed in 7:15:04.
14:30:30 Total time: 7:15:04
```

Om de local channel up to date te houden moet je nog een synchronisatie instellen. Klik op **Manage Software Channels** kies het tabblad **Repositories** en daaronder **Sync**.

[Selecteer Sync only latest packages](#) en stel een dagelijkse sync rond 5:00AM in:

> Software Channels

> Package Search

> Manage Software Channels

> Manage Software Packages

> Manage Repositories

> Distribution Channel Mapping

centos_7-x86_64

Delete software channel

Details

Managers

Errata

Packages

Repositories

Add / Remove

Sync

Channel Repositories

Last Sync Time

2017-02-11 20:30:30 CET

0 1 2 3 4 5 6 7 8 9

A B C D E F G H I J K L M N O P Q R S T U V W X Y Z

1 - 1 of 1

25 items per page

Repository	Sync Status
centos_7-x86_64-nlugg	

1 - 1 of 1

☐ Do not sync errata

☒ Sync only latest packages

☐ Create kickstartable tree

☐ Terminate upon any error

Sync Now

Select a schedule:

☐ Disable Schedule

☒ Daily

at

5:00 am

CET

4:30 am

5:00 am

5:30 am

6:00 am

6:30 am

☐ Weekly

Every

Sun

at

6:00 am

CET

☐ Monthly

Day

1

at

1:27 pm

CET

☐ Custom Quartz format

Schedule

Copyright © 2002-15 Red Hat, Inc. All rights reserved. Privacy statement : Legal statement : redhat.com

- <https://wiki.auriel.nl/>

Child Channels

Child channels maak je onder een base Channel aan om repositories te ontsluiten die specifiek bij de OS release van dat Base Channel horen, zoals in dit voorbeeld de updates en de EPEL repositories.

update child channel

Maak eerst een repository aan, dit gaat hetzelfde als de repository voor het base Channel.

Ga naar **Channels** en kies in het zij menu **Manage Software Channels** -> **Manage Repositories** en druk op **+Create Repository**

Vul een naam in en de URL

http://ftp.nluug.nl/ftp/pub/os/Linux/distr/CentOS/7/updates/x86_64/ en druk op de groene knop **Create Repository**

Maak vervolgens het Child Channel aan. Ga naar **Manage Software Channels** en druk op **+Create Channel** , vul alles in en kies deze keer een **Parent Channel**

 **SPACEWALK**

Knowledgebase Documentation admin  

Systems 

Overview Systems Errata Channels Audit Configuration 0 systems selected Manage Clear

Schedule Users

Admin Help

> Software Channels

> Package Search

> Manage Software Channels

> Manage Software Packages

> Manage Repositories

> Distribution Channel Mapping

Create Software Channel

Basic Channel Details

Create or edit software channels from this page.

If the parent channel is set to 'none', the channel is a base channel. Otherwise, the channel is a child of the specified channel.

Channel name and label are required.

They each must be at least 6 characters in length.

Channel name must not be longer than 256 characters and channel label must not be longer than 128 characters.

Channel name must begin with a letter and channel label may begin with a letter or digit.

They each must not begin with rhn, redhat or red hat.

They each must contain only lowercase letters, hyphens ('-'), periods ('.'), underscores ('_'), and numerals.

Channel name may also contain spaces, parentheses () and forward slashes ('/').

Channel summary is also required and must not exceed 500 characters.

Channel Name*:

Channel Label*:

Parent Channel:

Architecture:

Yum Repository Checksum Type:

Tip: sha1 offers the widest compatibility with clients. sha-256 offers higher security, but is compatible only with newer clients: Fedora 11 and newer, or Enterprise Linux 6 and newer.

Channel Summary*:

De GPG keys zijn hetzelfde, vul dus dezelfde waarden in al bij het Parent Channel en druk op de groene knop **Create Channel**:

Security: GPG

GPG key URL:

GPG key ID:

Example: DB42A60E

GPG key Fingerprint:

Example: CA20 8686 2BD6 9DFC 65F6 ECC4 2191 80CD DB42 A60E

[Create Channel](#)

Copyright © 2002-15 Red Hat, Inc. All rights reserved. [Privacy statement](#) : [Legal statement](#) : [redhat.com](#)

Spacewalk release 2.6



Ga vervolgens naar het tabblad **Repositories**, selecteer de net aangemaakte repository voor updates, en druk op **Update Repositories**

Log in op de server en doe `spacewalk-repo-sync -c centos_7-x86_64-updates`

```
14:15:16 =====
14:15:16 | Channel: centos_7-x86_64-updates
14:15:16 =====
14:15:16 Sync of channel started.
14:15:17 Repo URL:
http://ftp.nluug.nl/ftp/pub/os/Linux/distr/CentOS/7/updates/x86_64/
14:15:18 Packages in repo:          807
14:15:19 Packages already synced:    0
14:15:19 Packages to sync:            807
14:15:19 1/807 : 389-ds-base-1.3.5.10-12.el7_3-0.x86_64
14:15:31 2/807 : 389-ds-base-1.3.5.10-15.el7_3-0.x86_64
...
...
```

Stel nog wel een dagelijkse sync in: Ga naar het subtabblad **Sync** selecteer **Daily**, kies een tijdstip en druk op **schedule**

Andere child channels

We nemen als voorbeeld de populaire EPEL repository. Nagenoeg hetzelfde als de update child channel.

Maak eerst een repository aan, ga naar **Channels** en kies in het zij menu **Manage Software Channels** -> **Manage Repositories** en druk op **+Create Repository**

Vul een naam in `epel_7-x86_64-nluug` en de URL http://ftp.nluug.nl/pub/os/Linux/distr/fedora-epel/7/x86_64/ en druk op de groene knop **Create Repository**

Maak vervolgens het Child Channel aan `epel_7-x86_64`. Ga naar **Manage Software Channels** en druk op **+Create Channel**, vul alles in en kies deze keer een **Parent Channel** in dit geval `centos_7-x86_64`

De GPG key moet je weer downloaden en analyseren om die vervolgens in te vullen. `cd /tmp`
`wget http://ftp.nluug.nl/pub/os/Linux/distr/fedora-epel/RPM-GPG-KEY-EPEL-7`
`gpg --with-fingerprint RPM-GPG-KEY-EPEL-7`

```
pub 4096R/352C64E5 2013-12-16 Fedora EPEL (7) <epel@fedoraproject.org>  
Key fingerprint = 91E9 7D7C 4A5E 96F1 7F3E 888F 6A2F AEA2 352C 64E5
```

druk op **Create Channel**.

Vervolgens de repository aan dit channel koppelen: Ga naar het tabblad **Repositories**, selecteer `epel_7-x86_64-nluug` en druk op **Update Repositories**

log in op de server en doe `spacewalk-repo-sync -c epel_7-x86_64`

stel nog een sync schedule in en klaar.

En Verder

Nu je je channels klaar hebt is het tijd om clients te koppelen.

Bronnen

<http://www.unixmen.com/how-to-manage-spacewalk-channels-and-repositories/>

<https://www.redhat.com/archives/spacewalk-list/2012-January/msg00105.html>

<https://easyitstuff.wordpress.com/2015/08/17/how-to-create-spacewalk-channel/>

From:
<https://wiki.auriel.nl/> -

Permanent link:
https://wiki.auriel.nl/doku.php?id=werkinstructies:spacewalk_channels&rev=1486908973

Last update: **2017/02/12 15:16**

